METHOD AND APPARATUS OF DETERMINING DEFECT-FREE

SEMICONDUCTOR INTEGRATED CIRCUIT

5 BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a method of

determining a defect-free semiconductor integrated

circuit such as complementary metal oxide semiconductor

10 (CMOS) integrated circuit.

2. Description of the Related Art

Many of semiconductor integrated circuits (ICs)

are simultaneously formed on a semiconductor wafer by a

same design rule, and in same production conditions.

15 However, all of the ICs are always defect-free, and the

inspection for the ICs is required. Many inspection

methods have been proposed.

Japanese Unexamined Patent Publication (Kokai)

No. 8-271584, Japanese Unexamined Patent Publication

20 (Kokai) No. 9-211088, U.S. Patent No. 5392293, U.S.

Patent No. 5519333, and U.S. Patent No. 5889408 describe

a quiescent power supply current (QPSC, I_{DDQ}) of a CMOS

integrated circuit which is a test using an I_{DDQ}.

In an I_{DDQ} test, the measurement of the

25 quiescent power supply current of a CMOS integrated

circuit (IC) is carried out and the determination of

defective or indefectible (defect-free) CMOS integrated

circuit is carried out based on the measured value. Note

that the CMOS integrated circuit to be tested is also

5   called a "IC device under test" (DUT).

The quiescent power supply current I_{DDQ} many

include a leakage current flowing even in a defect-free

(indefectible) device called as "an intrinsic leakage

current" or "a normal leakage current") and a defect

10   current occurring due to a defect in the DUT. That is,

the quiescent power supply current I_{DDQ} is defined as the

total of the normal leakage current and the defect

current.

The normal leakage current can be expressed by

15   the total of the leakage current (FET leakage current)

generated from the structure of the metal oxide

semiconductor field effect transistors (MOSFETs) and the

leakage current (circuit leakage current) occurring due

to circuit operation . The circuit leakage current may be

20   generated by analog circuits, pull-up circuits, bus

collision, etc.

In an I_{DDQ} test measuring the quiescent power

supply current of a CMOS integrated circuit (IC) device

and determining an IC device to be defective when the

25   measured value is more than a threshold value, as

described in T. W. Williams, R.H. Dennard, and R. Kapur, "Iddq Test: Sensitivity Analysis of Scaling", in *Int. Test Conf.*, pp. 786-792, IEEE, 1996, accurate determination is sometimes difficult. The reason is, for

5   example, when the interconnection patterns in an CMOS integrated circuit are extremely fine, the leakage current of the MOSFETs (FET leakage current) increases exponentially along with the fineness. Therefore, various methods have been proposed to reduce the FET leakage

10   current during an I_{DDQ} test.

As a method for reducing the FET leakage current during an I_{DDQ} test, there is known the method of lowering the threshold value by lowering the FET leakage current when strobing. As such the method, a low power

15   supply voltage method, low temperature measurement method, and well bias method are known.

Low Power Supply Voltage Method

This method is a reduction method by utilizing the fact that the leakage current falls when the power

20   supply voltage V_D is lowered. In this method, however, the lowering of the power supply voltage V_D is limited to an extent where no circuit malfunction occurs, so the rate of reduction of the FET leakage current is low. Also, raising or lowering the power supply voltage V_D

25   before and after strobing takes several milliseconds

(msec), so it takes a long test time, as a result, the cost increases along with this increase in the testing time.

According to A.E. Gattiker and W. Maly, "Toward Understanding 'Iddq-Only' Fails", in *Int. Test Conf.*, pp. 174-183, IEEE, 1998, a failure pass-through current may disappear when the power supply voltage V_D is lowered, and the test may not be achieved.

<u>Low Temperature Measurement Method</u>

This method is a reduction method by using the fact that the FET leakage current falls when the operating temperature is lowered.

The lower limit temperature is determined by the guarantee of reliability and the costs of a temperature apparatus system for maintaining a low temperature and the test apparatus, but with consumer use temperature apparatuses for maintaining low temperatures, about 0°C is the limit, as the rate of reduction of the FET leakage current is low. Further, the expense and running costs of the temperature apparatus are high, so the total test cost rises.

<u>Well Bias Method</u>

The well bias method is described in A. Keshavarzi, K. Roy, and C.F. Hawkins, "Intrinsic Leakage in Low Power Deep Submicron CMOS ICs", in *Int. Test*

Conf., pp. 146-155, IEEE, 1997.

In this reduction method, wiring for supplying the bias voltage is added, so the chip area of the CMOS integrated circuit increases or the integration may be

5 low.

Further, the rate of reduction of the leakage current in this method is strongly dependent on the variability of the effective gate length Leff, so the FET leakage current may be varied along with miniaturization.

10 Note that A. Keshavarzi, C.F. Hawkins, K. Roy, and V. De, "Effectiveness of Reverse Body Bias for Low Power CMOS Circuits", in *8th NASA Symposium on VLSI Design,* pp. 2.3.1-2.3.9, Oct. 1999, the rate of reduction is 1/5 when the effective gate length Leff is 0.18 μm,

15 while the rate of reduction is ½ when the effective gate length Leff is 0.13 μm.

As a test method for a CMOS integrated circuit, in addition to test methods using a fixed threshold value, there are known the Delta method and current ratio

20 method.

<u>Delta Method</u>

The Delta method is described in A.C. Miller, "Delta I_{DDQ} Testing", in U.S. Patent No. 5889408, March 1999. In this method, the test is conducted while

25 providing an upper limit on the difference between the

minimum value and maximum value of the I_{DDQ}. Since upper limit values are not set individually for CMOS integrated circuits, the overlooked defect current may be large. Further, a defect current of an extent less than the

5 amount of fluctuation between vector points (measurement points) of the normal leakage current may not be detected.

Current Ratio Method

The current ratio method is disclosed in

10 Japanese Unexamined Patent Publication (Kokai) No. 2000-171529. In this method, the test is conducted while making the ratio of the minimum value and maximum value of the I_{DDQ} a fixed ratio and setting an upper limit, so an overlooked defect current may occur due to the defect

15 current occurring at all vector points. Further, sometimes it is not possible to detect a defect current of an extent less than the amount of fluctuation between vector points of the normal leakage current.

Note, the power supply current of a CMOS

20 integrated circuit can be divided into a transient current at the time of switching and a quiescent current at the time of quiescence. In an I_{DDQ} test, generally the quiescent current at the time of quiescence is measured to determine defective or indefectible (defect-free) of

25 the CMOS integrated circuit.

In the I_{DDQ} tests of the related art, it is
assumed that the I_{DDQ} is the leakage current (FET leakage
current) in the FETs.

In recent years, it has become important to
5   integrate a plurality of devices of different designs on
a single chip in order to reduce the size of portable
devices and reduce costs through integration.

Therefore, a need has arisen for I_{DDQ} testing a
CMOS integrated circuit with a circuit(s) having a
10 current(s) (circuit leakage current(s)) due to pull-up,
pull-down, and bus collision.

SUMMARY OF THE INVENTION

An object of the present invention is to provide a
15 method and apparatus of determining a defect-free
semiconductor integrated circuit able to determine a
defective or indefectible (defect-free) circuit
regardless of the existence of a circuit leakage current.

According to a first aspect of the present
20 invention, there is provided a method of determining a
defect-free or defect semiconductor integrated circuit,
comprising: a first measurement step for measuring a
quiescent power supply current (QPSC) of a first
semiconductor integrated circuit (IC), a plurality of
25 times in a predetermined interval after stop of the

operation of the first IC; a first data calculation step
for calculating a first feature data indicating a
feature(s) of the measured QPSCs of the first IC; a
second measurement step for measuring a QPSC of a second

5   semiconductor IC, a plurality of times in the same
condition to that of the first IC after stop of the
operation of the second IC; a second data calculation
step for calculating a second feature data indicating a
feature(s) of the measured QPSCs of the second IC; and a

10   comparison and determination step for comparing a
resemble between the first feature data and the second
feature data, and determining the first and second ICs as
defect-free ICs when the resemble is high or the first
and second ICs as defect ICs when the resemble is low.

15   The first and second ICs may be formed on the same
semiconductor wafer.

        Preferably, the IC comprises a complementary metal
oxide semiconductor (CMOS) IC.

        preferably, one of the first and second ICs is

20   decided as a reference IC, the second measurement step
and the second calculation step are carried out for other
semiconductor IC as the second IC, in the comparison and
determination step, the second IC is determined as a
defect-free IC when the resemble is high, or as a defect

25   IC when the resemble is low.

Preferably, in the first data calculation step, a

first average QPSC of the measured QPSCs of the first IC

and a first plurality of QPSC deviations of the measured

QPSCs of the first IC which are (measured QPSCs of the

5   first IC - the first average) are calculated, and in the

second data calculation step, a second average QPSC of

the measured QPSCs of the second IC and a second

plurality of QPSC deviations of the measured QPSCs of the

second IC which are (the measured QPSCs of the second IC

10   - the second average) are calculated. The method may

further comprise a third data calculation step for

performing a first regression analysis on the first

plurality of QPSC deviations and the second plurality of

QPSC deviations to produce a first regression line and

15   calculating a gradient of the first regression line,

performing a second regression analysis on the measured

QPSCs of the first IC to produce a second regression line

and calculating a predicted QPSC, and calculating a

decision coefficient defined by the following formula.

$$1 - \frac{\sum (measured\ QPSCs\ of\ the\ second\ IC - predected\ QPSC)^2}{\sum (second\ deviation)^2}$$

20

In the comparison and determination step, the first and

second ICs are resemble when the decision coefficient is

greater than a limit value, and the deviation of the

gradient and the ratio is in a predetermined range.

Alternatively, in the first data calculation step, a first average QPSC of the measured QPSCs of the first IC, a first standard deviation of the measured QPSCs of the first IC, and first normalized values defined as (the measures QPSCs of the first IC - the first average)/the first standard deviation are calculated, and in the second data calculation step, a second average of the measured QPSCs of the second IC, a second standard deviation of the measured QPSCs of the first IC, and second normalized values defined as (the measures QPSCs of the second IC - the second average)/the second standard deviation are calculated. The method may further comprise a third data calculation step for performing a first regression analysis on the first plurality of normalized values and the second plurality of normalized values to produce a first regression line and calculating a gradient of the first regression line, performing a second regression analysis on the first normalized values to produce a second regression line and calculating a predicted normalized value, calculating an average normalized value of the second plurality of normalized values, and calculating a decision coefficient defined by the following formula.

$$1 - \frac{\sum \left(\sec ond \ s\tan dard \ values - predected \ s\tan dard \ value\right)^2}{\sum \left(\sec ond \ s\tan dard \ values - average \ s\tan dard \ value\right)^2}$$

In the comparison and determination step, the first and second ICs are resemble when the decision coefficient is greater than a limit value, and the gradient is in a predetermined range.

Alternatively, in the first data calculation step, a first average QPSC of the measured QPSCs of the first IC, a first standard deviation of the measured QPSCs of the first IC, and a first feature value defined by (the first average QPSC / the first standard deviation) are calculated, in the second data calculation step, a second average QPSC of the measured QPSCs of the second IC, a second standard deviation of the measured QPSCs of the second IC, and a second feature value defined by (the second average QPSC / the second standard deviation) are calculated, and in the comparison and determination step, the first and second ICs are resemble when the first and second feature values are in a predetermined range.

Alternatively, in the first data calculation step, a first average QPSC of the measured QPSCs of the first IC, first QPSC deviations which are (the measured QPSCs of the first IC - the first average QPSC), and first feature values defined by (the first QPSC deviations / the first

QPSC) are calculated, the second data calculation step, a second average QPSC of the measured QPSCs of the second IC, second QPSC deviations which are the measured QPSCs of the second IC - the second average QPSC, and second feature values defined by (the second QPSC deviations / the second QPSC average) are calculated, in the comparison and determination step, the first and second ICs are resemble when the first and second feature data are in a predetermined range.

According to a second aspect of the present invention, there is provided a method of determining a defect-free or defect semiconductor integrated circuit, comprising: a first measurement step for measuring each quiescent power supply current (QPSC) of each of a plurality of reference semiconductor integrated circuits (ICs), a plurality of times in a predetermined interval after stop of the operation of the first IC; a first data calculation step for calculating each first QPSC average of measured QPSCs of each reference IC, each first standard deviation of the measured QPSCs of each reference IC, each of first normalized values defined by ((the measured QPSCs - the corresponding first QPSC average) / the corresponding first standard deviation), each of first average normalized value of each of first normalized values, each of first feature value defined by

((each of the measured QPSCs - the corresponding each

first QPSC average) - (the corresponding each first

normalized values / the corresponding each first standard

deviation)), and the maximum feature value among the

5   first feature values; a second measurement step for

measuring a QPSC of a test IC a plurality of times in the

same conditions to the reference ICs after stop of the

operation of the test IC; a second data calculation step

for calculating a second QPSC average of measured QPSCs

10   of the test IC, a second standard deviation of the

measured QPSCs of the test IC, second normalized values

defined by ((the measured QPSCs of the test IC - the

second QPSC average) / the second standard deviation), a

second average normalized value of the second normalized

15   values, and second feature values defined by ((the

measured QPSCs of the test IC - the second average QPSC)

- (the second normalized values / the second standard

deviation)); a comparison and determination step for

comparing the second feature value and the maximum

20   feature value and determining the test IC as a defect-

free IC when the second feature values is smaller than

the maximum feature value or a defect IC when one of the

second feature values exceeds the maximum feature value.

      According to a third aspect of the present

25   invention, there is provided a method of determining a

defect-free or defect semiconductor integrated circuit,

comprising: a first measurement step for measuring a

quiescent power supply current (QPSC) of a reference

semiconductor integrated circuit (IC), a plurality of

5   times in a predetermined interval after stop of the

operation of the reference IC; a first data calculation

step for calculating a first standard deviation of

measured QPSCs of the reference IC; a second measurement

step for measuring a QPSC of a test IC a plurality of

10   times in the same condition of that of the reference IC

after stop of the operation of the test IC; a second data

calculation step for calculating a QPSC average and a

second standard deviation of measured QPSCs of the test

IC, and a comparison and determination step for comparing

15   a parameter which is ((QPSC average - (the second

standard deviation / the first standard deviation)) and a

limit and determining the test IC as a defect-free IC

when the parameter is smaller than the limit or the test

IC as a defect IC when the parameter is equal or greater

20   than the limit.

According to a fourth aspect of the present

invention, there is provided a method of determining a

defect-free or defect semiconductor integrated circuit,

comprising: a first measurement step for measuring each

25   quiescent power supply current (QPSC) of each of a

plurality of reference semiconductor integrated circuits

(ICs), a plurality of times in a predetermined interval

after stop of the operation of the first IC; a first data

calculation step for calculating each first QPSC average

5   of measured QPSCs of each reference IC, each first

standard deviation of the measured QPSCs of each

reference IC, and each of first coefficients defined by

((the measured QPSCs - the corresponding first QPSC

average) / the corresponding first standard deviation); a

10   second measurement step for measuring a QPSC of a test IC

a plurality of times in the same conditions to the

reference ICs after stop of the operation of the test IC;

a second data calculation step for calculating a first

QPSC average of measured QPSCs of the test IC, and second

15   deviations defined by (the measured QPSCs of the test IC

- the first QPSC average); a third data calculation step

for performing regression analysis on the first

coefficients and the second deviations to produce a

regression analysis, calculating a predicted coefficient

20   from the regression line and a gradient of the regression

line, and calculating a decision coefficient by the

following formula, and

$$1 - \frac{\sum \left(\textit{the first coefficients} - \textit{the predected coefficient} \right)^2}{\sum \left(\textit{the} \sec \textit{ond deviations} \right)^2}$$

a comparison and determination step for comparing the

test IC as a defect-free IC when the decision coefficient

is greater than a limit and (the gradient / the second

deviations) are in a predetermined range.

5   According to a fifth aspect of the present

invention, there is provided a method of determining a

defect-free or defect semiconductor integrated circuit,

comprising: a first measurement step for measuring each

quiescent power supply current (QPSC) of each of a

10   plurality of reference semiconductor integrated circuits

(ICs), a plurality of times in a predetermined interval

after stop of the operation of the first IC; a first data

calculation step for calculating each first QPSC average

of measured QPSCs of each reference IC, each first

15   standard deviation of the measured QPSCs of each

reference IC, each of first normalized values defined by

((the measured QPSCs - the corresponding first QPSC

average) / the corresponding first standard deviation),

each of first average normalized value of each of first

20   normalized values, and each of first feature value

defined by ((each of the measured QPSCs - the

corresponding each first QPSC average) - (the

corresponding each first normalized values / the

corresponding each first standard deviation)); a second

25   measurement step for measuring a QPSC of a test IC a

plurality of times in the same conditions to the

reference ICs after stop of the operation of the test IC;

a second data calculation step for calculating a second

QPSC average of measured QPSCs of the test IC, a second

5   standard deviation of the measured QPSCs of the test IC,

second normalized values defined by ((the measured QPSCs

of the test IC - the second QPSC average) / the second

standard deviation)), and second normalized value

deviation defined as (the second normalized values - the

10   average normalized values); a third data calculation step

for performing regression analysis on the first

coefficients and the second deviations to produce a

regression analysis, calculating a predicted feature

value from the regression line and a gradient of the

15   regression line, and calculating a decision coefficient

by the following formula, and

$$1 - \frac{\sum (\textit{the first feature values} - \textit{the predected feature value})^2}{\sum (\textit{the sec ond s} \tan \textit{dard values} - \textit{an average of the sec ond s} \tan \textit{dard value})^2}$$

a comparison and determination step for determining the

20   test IC as a defect-free IC when the decision coefficient

is greater than a limit and the gradient is in a

predetermined range.

According to the present invention, there is

provided apparatuses for carrying out above methods.

BRIEF DESCRIPTION OF THE DRAWINGS

These and other objects and features of the present invention will become clearer from the following description of the preferred embodiments given with

5   reference to the attached drawings, wherein:

FIG. 1 is a first explanatory view illustrating the case where vector waveforms resemble each other between defect-free CMOS integrated circuits;

FIG. 2 is a second explanatory view illustrating the

10   case where vector waveforms resemble each other between defect-free CMOS integrated circuits;

FIG. 3 is a third explanatory view illustrating the case where vector waveforms resemble each other between defect-free CMOS integrated circuits;

15   FIG. 4 is a plot graph view of an example of the distribution of plotted points showing deviations at different vector points for two CMOS integrated circuits sampled from a plurality of CMOS integrated circuits under test;

20   FIG. 5 is a plotted graph of an example of the distribution of plotted points showing a mean value of a plurality of measured values of a quiescent power supply current and a standard deviation for approximately 800 CMOS integrated circuits passing a scan test;

25   FIG. 6 is a graph illustrating the distribution of

reciprocals $(1/\sigma_R)$ of standard deviations of proportional

coefficients R_i for the group of a plurality of CMOS

integrated circuits of FIG. 5;

FIG. 7 is a plotted graph of an example of

5 distribution of plotted points showing a mean value of a

measured value of quiescent power supply current and

deviation for approximately 800 CMOS integrated circuits;

FIG. 8 is a plotted graph illustrating the

distribution of plotted points showing a standard

10 deviation and predicted error for defect-free CMOS

integrated circuits;

FIG. 9 is a view showing a configuration of a tester

using the method of determination of a defect-free CMOS

integrated circuit of an embodiment according to the

15 present invention;

FIG. 10 is a flow chart of computer processing in

the tester of FIG. 9 and shows an embodiment of a method

for selection out defect-free CMOS integrated circuits;

FIG. 11 is a flow chart of a first embodiment of

20 processing for inspection of resemblance;

FIG. 12 is a flow chart of a second embodiment of

processing for inspection of resemblance;

FIG. 13 is a flow chart of a third embodiment of

processing for inspection of resemblance;

25 FIG. 14 is a flow chart of a fourth embodiment of

processing for inspection of resemblance;

FIG. 15 is a flow chart of computer processing in the tester in FIG. 9 and shows a first embodiment of a method for determining defect of a CMOS integrated

5 circuit;

FIG. 16 is a flow chart of computer processing in the tester in FIG. 9 and shows a second embodiment of a method for determining defect of a CMOS integrated circuit;

10 FIG. 17 is a flow chart of computer processing in the tester in FIG. 9 and shows a third embodiment of a method for determining defect of a CMOS integrated circuit;

FIG. 18 is a flow chart of computer processing in

15 the tester in FIG. 9 and shows a fourth embodiment of a method for determining defect of a CMOS integrated circuit;

FIG. 19 is a flow chart of computer processing in the tester in FIG. 9 and shows a fifth embodiment of a

20 method for determining defect of a CMOS integrated circuit; and

FIG. 20 is a flow chart of computer processing in the tester in FIG. 9 and shows a sixth embodiment of a method for determining defect of a CMOS integrated

25 circuit.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

Preferred embodiments of the present invention will be described in detail below with reference to the attached figures.

5   First, a basic concept of the present invention will be described and preferred embodiments will be described.

One example of a semiconductor integrated circuit (IC) of the present invention is referred to a CMOS IC.

Defect-free CMOS Integrated Circuit

10   In a CMOS IC, circuit leakage current and deep submicron (ICs of gate length of under 0.25 μm) FET leakage current sometimes exhibit values of more than several hundred μA. These leakage currents often differ for individual CMOS integrated circuits due to the

15   variability of manufacturing conditions even for CMOS integrated circuits of the same design and formed on the same semiconductor wafer.

Further, the circuit leakage current may change at each vector point (strobe point) due to the changes in

20   internal nodes depending on the test pattern, and the FET leakage current may change due to a drain induced barrier lowering (DIBL) and/or a gate inducted drain leakage (GIDL). Regarding on this matter, reference may be made to M.C. Johnson, D. Somasekhar, and K. Roy, "Models and

25   Algorithms for Bounds on Leakage in CMOS Circuits", in

IEEE Tran. CAD IC Sys., vol. 18, no. 6, pp. 714-725, June

1999.

In this embodiment of the present invention, when

measuring the quiescent power supply circuit (QPSC) I_{DDQ}

5   in the CMOS IC, as the quiescent state, a clock applied

to the CMOS IC is held from the time of end of switching

of the test pattern, the current value after a

predetermined time passes and the current stabilizes is

measured several times at a predetermined interval. It is

10   assumed that the measured current may include current

other than the FET leakage current.

The reason why the measurement of the several times

of the QPSC is preferable, is that the QPSC may vary in

the elapse of the time even in the quiescent state of the

15   CMOS IC.

In the specification, the measurement points are

called as vector points.

When assigning serial numbers to the vector points

(measurement points) and preparing a plotted graph of the

20   distribution of plotted points showing vector points and

measured current values at those vector points, the

vector waveforms comprised of lines connecting the

plotted points in the order of their serial numbers can

be considered to often resemble or approximately resemble

25   each other between defect-free CMOS integrated circuits.

- 23 -

FIG. 1 to FIG. 3 are explanatory views illustrating cases of vector waveforms resembling each other between defect-free CMOS integrated circuits. Note that in FIG. 1 to FIG. 3, the abscissa indicates the serial numbers i of

5 the vector points, the ordinate shows the current values I_{Li} of the quiescent power supply current, and there are a total of 20 vector points in each CMOS integrated circuit.

FIG. 1 is a view illustrating the relationship

10 between vector points showing measurement points for measuring the quiescent power supply current and the measured value of the quiescent power supply current at the vector points in two defect-free CMOS integrated circuits Die-A and Die-B. This drawing shows vector

15 waveforms comprised of bent lines connecting the plotted points.

Note that the O marks (circles) correspond to the measured value of the quiescent power supply current at the vector points in the defect-free CMOS integrated

20 circuit Die-A, while the Δ marks (triangles) correspond to the measured value of the quiescent power supply current at the vector points of the defect-free CMOS integrated circuit Die-B.

FIG. 2 is a view of the case when the vector

25 waveforms of FIG. 1 are shifted to be superposed.

FIG. 3 is a view of the case when the vector

waveform of the Die-B in FIG. 1 is enlarged in the

vertical direction and the enlarged vector waveform and

the vector waveform of the Die-A are superposed. The

5   vector waveforms overlap and coincide. In this way, the

vector waveforms of the defect-free CMOS integrated

circuits Die-A and Die-B shown in FIG. 1 to FIG. 3

resemble each other. Further, it is possible to sort out

the defect-free CMOS integrated circuits using this

10   resemblance.

In the present invention, by using the resemblance

of two semiconductor ICs, more specifically, by using the

resemblance of two feature data (or feature parameters)

such as the vector waveforms obtained from the measured

15   quiescent power supply currents (QPSCs) of two

semiconductor ICs, a defect-free IC can be determined. If

the both feature data are resemble, the both IC are

defect-free. If the defect-free IC is found, other ICs

can be tested by using the found defect-free IC as a

20   reference IC.

A variety of the determination methods by using the

resemblance of the present invention will be described

below.

Considering the resemblance of the vector waveforms

25   of defect-free CMOS integrated circuits, a quiescent

power supply current I_{DDQ} of a defect-free CMOS integrated

circuit, that is, a normal leakage current I_{Li}, is

expressed by the following equation (1). Note that in

equation (1), R_i is a proportional coefficient, and $\underline{i}$ is

5   the index of the vector point.

$$I_{Li} = R_i \cdot Ip + I_{AL} \qquad (1)$$

In equation (1), the relationship of the following

equation (2) stands between a current parameter Ip and a

10 constant current in the whole vector points I_{AL} and the

mean (average) value I_ℓ of the normal leakage currents

I_{Li}.

$$I_\ell = Ip + I_{AL} \qquad (2)$$

15 <u>Measured Current and Defect Current</u>

In a CMOS integrated circuit existing a defect

current, a measured value I_{Qi} of the quiescent power

supply current measured at each vector point is expressed

by the following equation (3), namely, the total of the

20 normal leakage current I_{Li}, the defect current I_{RDi}

occurring independently or randomly at each vector point,

and the constant defect current I_{SD} occurring similarly

at each vector point.

$$I_{Qi} = I_{Li} + I_{RDi} + I_{SD} \qquad (3)$$

25

Defect-Free Device Selection

To determine defect or indefectibly (defect-free) CMOS integrated circuits, it is desirable to collect defect-free CMOS integrated circuits in advance. This collecting of defect-free CMOS integrated circuits is called as "defect-free device selection".

Normally, many CMOS ICs are formed in a same semiconductor wafer. A plurality of defect-free CMOS ICs used for reference ICs are selected among many CMOS ICs, and other CMOS ICs are tested by using such reference ICs.

Of course, it is not always required such the many reference ICs, and it is enough by selecting at least one reference (defect-free) IC.

Note, the defect-free device sorting can be applied to the defect-free or defect IC detection.

Defect-Free Device Selection - 1

A deviation I_{DLi} is expressed by the following equation (4) by using the normal leakage current I_{Li} at each vector point $\underline{i}$ (i = 1 to n) in a defect-free CMOS integrated circuit and the mean value I_ℓ of the currents. Note that when the total number $\underline{n}$ of the vector points is made a plurality of points, the mean value $I_\ell = (I_{L1}+I_{L2}+ \cdot \cdot \cdot +I_{Ln})/n$.

$$I_{DL1} = I_{Li}-I_\ell \qquad\qquad (4)$$

By substituting the normal leakage current I_{L1} of
the above equation (1) and the mean value I_ℓ of the above
equation (2) into the above equation (4), the following
equation (5) is obtained.

5
$$I_{DL1} = (R_i \cdot Ip + I_{AL}) - (Ip + I_{AL})$$
$$= (R_i - 1) \cdot Ip \qquad (5)$$

The ratio of deviations at vector points for two
defect-free CMOS integrated circuits X and Y is shown by
10 the following equation (6).
$$I_{DLyi}/I_{DLxi} = \{(R_i-1) \cdot Ipy\}/\{(R_i-1) \cdot Ipx\}$$
$$= Ipy/Ipx \qquad (6)$$

The parameters Ip and deviations I_{DL1} of the two
15 defect-free CMOS integrated circuits are made the
parameter Ipx and the deviation I_{DLxi} for the CMOS
integrated circuit X and made the parameter Ipy and
deviation I_{DLyi} for the CMOS integrated circuit Y.

In this way, when the CMOS integrated circuits X and
20 Y are defect-free, the ratio of the deviations (I_{DLyi}/I_{DLxi})
of the normal leakage flows is constant regardless of the
vector points. The ratio of deviations (I_{DLyi}/I_{DLxi}) is made
equal to S_A, $S_A = I_{DLyi}/I_{DLxi}$.

FIG. 4 is an explanatory view plotting the
25 deviations at each vector point for two CMOS integrated

circuits X and Y extracted from a plurality of CMOS

integrated circuits under test. The defect-free device is

shown by the O marks (circles), while the defective

device is shown by the Δ marks (triangles).

5   Namely, when the both CMOS IC X and Y are defect-

free, the normal leakage current deviations I_{DLxi} and I_{DLyi}

are plotted in an orthogonal coordinates to obtain a

substantially strait line RL having a gradient (slant)

SA. The line RL is called as a regression (recursive)

10   line.

The gradient S_A can be obtained by, for example, a

root mean square method.

When the two sampled CMOS integrated circuits X and

Y are defect-free, the plotted points of the normal

15   leakage current deviations I_{DLxi} and I_{DLyi} form a line

(regression line). The slant of this line is S_A.

Predicted values y_{Hi} of the quiescent power supply

current of the CMOS IC will be calculated by using the

regression line and the slant S_A, as described below.

20   A decision coefficient (correlation coefficient,

residual square) r^2 showing the correlation between two

CMOS integrated circuits is expressed by the following

equation (7). When the two CMOS integrated circuits are

defect-free, the value of r^2 is 1 or substantially 1.

$$r^2 = 1 - \frac{\sum_{i=1}^{n} (y_i - y_{Hi})^2}{\sum_{i+1}^{n} (y_i - y_A)^2} \qquad \ldots \quad (7)$$

5   Note that in the above equation (7), y_i indicates
the measured values of the quiescent power supply current
of the CMOS integrated circuit Y at a vector point $\underline{i}$, Y_A
is the mean (average) value of the measured value y_i (=
I_{Qyi}), and Y_{Hi} is the predicted values obtained by

10   predicting the measured values y_i using the regression
line from the measured value x_i (= I_{Qxi}) of the quiescent
power supply current (QPSC) of the CMOS integrated
circuit X at the vector point $\underline{i}$. The actual measured
value y_i of the QPSC of the CMOS IC Y is called as an

15   actual value.

Specifically, when the measured value y_i of the
quiescent power supply current of the CMOS integrated
circuit Y can be approximated by

$$Y_i \fallingdotseq C + S_A \cdot x_i, \qquad \ldots \quad (7\text{-}1)$$

20

the predicted value y_{Hi} is expressed by the regression
equation

$$Y_{Hi} = c + S_A \cdot x_i \qquad \ldots \quad (7\text{-}2)$$

25   The term $\underline{c}$ in the regression equation indicates a

constant.

The smaller the difference between the measured value y_i and the predicted value y_{Hi}, the smaller the deviation from the predicted value shown. Therefore, it is possible to use the above equation (7) to calculate the decision coefficient r^2 and use this decision coefficient r^2 as a yardstick for applicability (matching) of the regression equation.

Note that for regression analysis, reference may be made to Takemura, *Kyoritsu Seminar on Mathematics in the 21st Century - 14: Statistics*, pp. 36-37, Kyoritsu Publishing, 1997.

When one or both of the measured values of the quiescent power supply current of two CMOS integrated circuits includes a defect current I_{RDi}, the plot or plotted points of the measured value(s) is or are deviated from the regression line and the value of the decision coefficient r^2 becomes smaller.

In a defect-free CMOS integrated circuit, if $I_{AL} = 0$ in the above equations (1) and (2), when one or both of the two CMOS integrated circuits includes a certain defect current I_{SD}, the mean value Iq of the measured value I_{Qi} becomes larger than the mean value I_t of the normal leakage currents I_{Li} and the ratio (Iqy/Iqx) of the mean values Iqy and Iqx of the quiescent power supply

current of the two CMOS integrated circuits Y and X no longer coincides with the slant S_A of the regression line.

Then, in the two CMOS integrated circuits X and Y, when the condition that the decision coefficient r^2 is larger than the preset lower limit $L_{RA}{}^2$ and the condition that the difference $(S_A - Iqy/Iqx)$ between the ratio of the mean values of the quiescent power supply current and the slant S_A of the regression line is within a preset range, it is possible to determine that the two CMOS integrated circuits X and Y resemble each other in vector waveforms and sort out the circuits as defect-free circuit.

Defect-Free Device Selection - 2

A standard deviation σ_L of the normal leakage current I_{Li} of the above equation (1) is expressed by the following equation (8) using the standard deviation σ_R of a proportional coefficient R_i.

$$\sigma_L = \sigma_R \cdot Ip \qquad\qquad (8)$$

A normalized value R_{Li} of the normal leakage current I_{Li} is expressed by the following equation (9) using the mean value I_ℓ and the standard deviation σ_L.

$$R_{Li} = (I_{Li} - I_\ell)/\sigma_L \qquad\qquad (9)$$

The above equation (9) can be modified as in the

following equation (10) using equations (4) and (5).

$$R_{Li} = I_{DL1}/\sigma_L$$

$$= (R_i-1) \cdot Ip/\sigma_L \qquad (10)$$

5   The above equation (10) can be modified as in the following equation (11) using equation (8).

$$R_{Li} = (R_i-1) \cdot Ip/(\sigma_R \cdot Ip)$$

$$= (R_i-1)/\sigma_R \qquad (11)$$

10   From the above equation (11), the normalized value R_{Li} becomes the same value regardless of the magnitude of the normal leakage current I_{Li}. Therefore, when the two CMOS integrated circuits X and Y are defect-free, if finding the ratio of the normalized values at the vector

15   points, the value becomes 1 as shown in the following equation (12). Note that in the following equation (12), the normalized value of the normal leakage current of the CMOS integrated circuit X is named as R_{Lxi} and the normalized value of the normal leakage current of the

20   CMOS integrated circuit Y is named as R_{Lyi}.

$$R_{Lyi}/R_{Lxi} = \{(R_i-1)/\sigma_R\}/\{(R_i-1)/\sigma_R\}$$

$$= 1 \qquad (12)$$

On the other hand, the normalized value R_{Qi} of a

25   measured value I_{Qi} of the quiescent power supply current

including a defect current is expressed by the following

equation (13) using the standard deviation σ_Q and mean

value Iq of the measured value I_{Qi}.

$$R_{Qi} = (I_{Qi}-I_\ell)/\sigma_Q \qquad (13)$$

5

By using equation (3) for the above equation (13),

the following equation (14) is obtained. Note that the

mean value of the defect currents I_{RDi} is expressed by I_{rd}.

$$R_{Qi} = \{(I_{Li}+I_{RDi}+I_{SD})-(I_\ell+I_{rd}+I_{SD})]/\sigma_Q$$

10 $$= (I_{Li}-I_\ell+I_{RDi}-I_{rd})/\sigma_Q \qquad (14)$$

Since the change in the standard deviation σ_Q due to

the defect current I_{RDi} is small, the standard deviation

σ_Q can be approximated by the standard deviation σ_L of

15 the normalized value R_{Li} of the normal leakage current

I_{Li}. The above equation (14) can be modified to the

following equation (15) by this approximation.

$$R_{Qi} = (I_{Li}-I_\ell)/\sigma_L+(I_{RDi}-I_{rd})/\sigma_L$$

$$= R_{Li}+(I_{RDi}-I_{rd})/\sigma_L \qquad (15)$$

20

The mean values Iqx and Iqy and standard deviations

σ_{Qx} and σ_{Qy} are calculated and the normalized values R_{Qxi}

and R_{Qyi} are calculated from the measured values I_{Qxi} and

I_{Qyi} of the quiescent power supply current of the two CMOS

25 integrated circuits X and Y. Further, regression analysis

is performed on the normalized values (R_{Qxi} and R_{Qyi}) to

obtain the regression line.

The gradient S_B of the regression line by, for

example a root means square method, and predicted

5   normalized value R_{Hi} are obtained by using the gradient S_B

and the regression line, as shown in the formula (7-2).

Thereafter, a decision coefficient r_B^2 is calculated by

the following formula.

$$r_B^2 = 1 - \frac{\Sigma(R_{Qyi} - R_{Hi})^2}{\Sigma(R_{Qyi} - R_A)^2}$$

10   where, R_A is an average of R_{Qyi}.   ... (7A)

In the plotted graph of the normalized value R_{Qi},

due to the deviation of the normalized value R_{Qi} from the

regression line by the defect current I_{RDi}, the decision

15   coefficient r_B^2 becomes smaller, so it is possible to

select defect-free devices by setting a lower limit of

the decision coefficient r_B^2.

When the condition that the decision coefficient r_B^2

is larger than a preset lower limit L_{RB}^2 and the condition

20   that the difference (S_B-1) between the slant S_B of the

regression line and 1 is within a preset allowable range

are satisfied, it can be determined that the two CMOS

integrated circuits X and Y resemble each other in vector

waveform and the devices can be sorted out as defect-

free.

Defect-Free Device Selection - 3

By using equation (2), it is possible to modify equation (8) to the following equation (16).

5
$$\sigma_L = \sigma_R \cdot (I_\ell - I_{AL}) \tag{16}$$

By modifying the above equation (16), the following equation (17) is obtained.

$$I_\ell = I_{AL} + \sigma_L/\sigma_R \tag{17}$$

10

When preparing a plotted graph using the standard deviation σ_Q of the measured value I_{Qi} of the quiescent power supply current for CMOS integrated circuits under test as the abscissa and using the mean value Iq as the

15 ordinate, the plotted points corresponding to defect-free CMOS integrated circuits are positioned on a straight line (ideal line).

Therefore, it is possible to sort out CMOS integrated circuits corresponding to the plotted points

20 positioned in an allowable range from the ideal line (for example, an intermediate region between upper and lower parallel lines to the ideal line) among the CMOS integrated circuits under test as being defect-free circuits.

25 FIG. 5 is a plotted graph illustrating the

distribution between the mean value Iq and standard

deviation σ_Q of the measured value of the quiescent power

supply current and the standard deviation σ_Q for

approximately 800 CMOS integrated circuits passing a scan

5   test. Most of the plotted points corresponding to the

defect-free CMOS integrated circuits are positioned on or

near the line of Iq = 0.7+0.5·σ_Q (that is, the ideal

line).

Note that the plotted points of the x marks

10   correspond to the defective CMOS integrated circuits not

passing a functional test. The plotted points of the +

marks correspond to the defect-free CMOS integrated

circuits passing the functional test.

FIG. 6 is a graph of the reciprocals ($1/\sigma_R$) of the

15   standard deviations of the proportional coefficients R_i

for the group of CMOS integrated circuits of FIG. 5. In

this graph, the abscissa shows $1/\sigma_R$, while the ordinate

shows the frequency. The mean value of the distribution

is about 0.5, the standard deviation of the distribution

20   is about 0.02, and the mean value of the distribution

coincides with the slant 0.5 of the ideal line in FIG. 5.

Defect-Free Device Selection - 4

The equation (5) showing the deviation I_{DLi} of the

normal leakage current I_{Li} can be modified to the

25   following equation (18) using equation (2).

$$I_{DL1} = (R_i-1) \cdot (I_\ell - I_{AL})$$

$$= (R_i-1) \cdot I_\ell + (1-R_i) \cdot I_{AL} \qquad (18)$$

Here, if preparing a plotted graph of the

distribution of plotted points showing the deviation I_{DL1}

and mean value I_ℓ for defect-free CMOS integrated

circuits, the plotted points are positioned on or near

the line corresponding to the above equation (18).

The deviation I_{DQi} of a measured value I_{Qi} of the

quiescent power supply current including a defect current

I_{RDi} is expressed by the following equation (19) using

equations (3) and (18).

$$I_{DQi} = I_{Qi} - Iq$$

$$= (I_{Li}+I_{RDi}+I_{SD}) - (I_\ell + I_{rd} + I_{SD})$$

$$= I_{DL1} + I_{RDi} - I_{rd}$$

$$= (R_i-1) \cdot I_\ell + (1-R_i) \times I_{AL} + I_{RDi} - I_{rd} \qquad (19)$$

By substituting $I_\ell = I_\ell - I_{rd} - I_{SD}$ in the above equation

(19), the following equation (20) is obtained.

$$I_{DQi} = (R_i-1) \cdot (Iq - I_{rd} - I_{SD}) + (1-R_i) \cdot I_{AL} - I_{rd} + I_{RDi}$$

$$= (R_i-1) \cdot Iq + (1-R_i) \cdot (I_{AL}+I_{SD}) - R_i \cdot I_{rd} + I_{RDi} \qquad (20)$$

If preparing a plotted graph of the distribution of

the plotted points showing the deviation I_{DQi} and mean

value Iq for CMOS integrated circuits under test from the

difference between the above equation (20) and equation (18), when a measured current I_{Qi} includes a defect current, its plot is positioned deviated from the line corresponding to the above equation (18) (ideal line).

5   Therefore, it is possible to sort out the CMOS integrated circuits corresponding to plotted points positioned in an allowable range from the ideal line (for example, the intermediate region sandwiched between upper and lower parallel lines of the ideal line) among the

10   CMOS integrated circuits under test as being defect-free. This selection method is effective when the number of vectors is small.

FIG. 7 is a plotted graph illustrating the distribution of the mean value Iq and deviation $I_{DQi} = I_{Qi} -$

15   Iq(N=1) of the quiescent power supply current for about 800 CMOS integrated circuits. Most of the plotted points corresponding to the defect-free CMOS integrated circuits are positioned on or near the line of $I_{DQi} = 0.75 - 0.96 \cdot Iq$ (that is, the ideal line).

20   Note that the plotted points of the x marks correspond to the defective CMOS integrated circuits not passing a functional test. The plotted points of the + marks correspond to the defect-free CMOS integrated circuits passing the functional test.

25   <u>Predicted Error</u>

The normalized value R_{Li} is calculated for each of the plurality of defect-free CMOS integrated circuits obtained by the selection of defect-free circuits. The normalized values R_{Li} are averaged for the plurality of

5   CMOS integrated circuits to calculate the reference normalized value R_{Ni}. By using this normalized value R_{Ni} and equation (9), the predicted value J_{Li} of a normal leakage current I_{Li} can be obtained by the following equation (21).

10   $$J_{Li} = R_{Ni} \cdot \sigma_L + I_\ell \qquad\qquad (21)$$

The predicted error E_i is expressed by the following equation (22) using the measured value I_{Li}, mean value I_ℓ, and standard deviation σ_L of quiescent power supply

15   current of a defect-free CMOS integrated circuit on which the calculation of the standard deviation R_{Ni} was based.

$$\begin{aligned} E_i &= I_{Li} - J_{Li} \\ &= I_{Li} - I_\ell - R_{Ni} \cdot \sigma_L \end{aligned} \qquad\qquad (22)$$

20   FIG. 8 is a plotted graph illustrating the distribution of plotted points showing a standard deviation σ_L and predicted error E_i for defect-free CMOS integrated circuits. In FIG. 8, the predicted error E_i is less than about half of the standard error σ_L, that is,

25   the maximum value E_{MAX} is about half of the standard

deviation σ_L.

It is possible to find the maximum value E_{MAX} of the predicted error E_i for all vector points of defect-free CMOS integrated circuits in this way.

5   Determination of Defect or Defect-free

Defect or defect-free CMOS integrated circuit under test can be determined based on the features of a defect-free CMOS integrated circuit obtained by selection out defect-free circuits and the measured value I_{Qi} of

10   quiescent power supply current of the CMOS integrated circuit under test.

Determination of Defect or Defect-free - 1 (I_{RD} Test)

Consider an estimated error P_{Di} of the following

15   equation (23) for a CMOS integrated circuit under test based on equation (22). In this equation (23), the measured value I_{Qi}, mean value Iq, and standard deviation σ_Q of quiescent power supply current of the CMOS integrated circuit under test are used.

20        $P_{Di} = I_{Qi} - Iq - R_{Ni} \cdot \sigma_Q$ (23)

The mean value Iq of the measured value I_{Qi} is expressed by the following equation (24) using equation (3).

25        $Iq = I_{\ell} + I_{rd} + I_{SD}$ (24)

By applying equations (24), (3), and (22) to

equation (23), it is possible to obtain the following

equation (25).

$$P_{Di} = (I_{Li}+I_{RDi}+I_{SD}) - (I_{\ell}+I_{rd}+I_{SD}) - R_{Ni} \cdot \sigma_Q$$

5
$$\doteq I_{Li}-I_{\ell}-R_{Ni} \cdot \sigma_L+I_{RDi}-I_{rd}$$

$$= E_i+I_{RDi}-I_{rd} \qquad (25)$$

In the above equation (25), the standard deviation

σ_Q closes the standard deviation σ_L since the change due

10   to the defect current I_{RDi} is small.

In a defect-free circuit, the defect current I_{RDi} is

0 or substantially 0, so the condition for determination

of defect or defect-free can be expressed by the

following equation (26).

15       $$-E_{MAX}<P_{Di}<E_{MAX} \qquad (26)$$

The defect current I_{RDi} of a defective circuit is

expressed by the following equation (27) using the above

equation (25) when the predicted error $E_i = E_{MAX}$. The

20   value expressed by this equation (27) can be used as a

yardstick.

$$I_{RDi} = P_{Di}-E_{MAX}+I_{rd} \qquad (27)$$

Determination of Defect or Defect-free - 2 (I_{SD}

25   **Test)**

- 42 -

When there is no defect current I_{RDi} in the measured

value I_{Qi} of quiescent power supply current of a CMOS

integrated circuit, the measured value I_{Qi} is expressed

by the following equation (28) from equation (3).

5       $I_{Qi} = I_{Li} + I_{SD}$ (28)

The standard deviation σ_Q of a measured value I_{Qi} in

this case is equal to the standard deviation σ_L of the

normal leakage current I_{Li}, so the parameter Ip is

10 expressed by the following equation (29) from equation

(8).

        $Ip = \sigma_Q/\sigma_R$ (29)

The mean value Iq of the measured value I_{Qi} of the

15 above equation (28) is expressed by the following

equation (30) using equation (2).

        $Iq = I_\ell + I_{SD}$

            $= Ip + I_{AL} + I_{SD}$ (30)

20   From the above equations (30) and (29), the total

$(I_{AL} + I_{SD})$ of the DC components of the measured value I_{Qi} is

expressed by the following equation (31).

        $I_{AL} + I_{SD} = Iq - Ip$

            $= Iq - \sigma_Q/\sigma_R$ (31)

25

When the leakage current of a CMOS integrated circuit under test is only the FET leakage current, as shown by the following equation (32), the condition for a defect-free circuit may be made that the total $(I_{AL}+I_{SD})$

5 be less than the maximum value E_{MAX} of the predicted error E_i.

$$E_{MAX} > Iq - \sigma_Q/\sigma_R \qquad\qquad (32)$$

When the leakage current of a CMOS integrated

10 circuit under test includes a circuit leakage current and there is variability in the magnitude of the circuit leakage current due to variability in the manufacturing conditions, the condition of a defect-free circuit may be made that the variability be within the allowable range

15 of variability of the magnitude of the circuit leakage current.

Note, the ratio σ_Q/σ_R, where σ_Q is the standard deviation of the measured quiescent power supply current (QPSC) I_{Qi} of the test CMOS IC and σ_R is defined as $I_p =$

20 σ_Q/σ_R by the formula 29, is expressed as I_p, and thus the formula (32) is expressed as follows.

$$E_{MAX} > Iq - Ip \qquad\qquad \dots \ (32a)$$

$(I_q - I_p)$ is a deviation, namely, the

25 variation.

In the following equation (33), the upper limit L_{SE} corresponds to the allowable range.

$$L_{SE} > Iq - \sigma_Q/\sigma_R \qquad \qquad \dots \qquad (33)$$

5   Determination of Defect or Defect-free - 3

A coefficient $K_{Li} = (I_{Li} - I_\ell)/I_\ell$ corresponding to the deviation of the normal leakage current I_{Li} at each vector point is calculated in advance for a plurality of defect-free CMOS integrated circuits. The coefficients

10   K_{Li} are averaged for the plurality of CMOS integrated circuits to calculate an average coefficient K_{Ni}.

The coefficient $K_{Li} (= (L_{Li} - I_1)/I_1)$ is a normalized value of the normal leakage current deviation I_{PLi} by the average current I_1 of normal leakage current I_{Li}.

15   The calculation of the average coefficient K_{Ni} from the plurality of the coefficients K_{Li} is intended to increase an accuracy of the coefficient K_{Ni}. Therefore, the coefficient K_{Li} of one reference CMOS IC can be applied in the following descriptions and equations.

20   Next, the mean value Iq and deviation $I_{DQi} (= I_{Qi} - Iq)$ are calculated from the measured value I_{Qi} of a CMOS integrated circuit under test.

The regression analysis is performed on the coefficient K_{Ni} and the deviation I_{PQi} of the measured

25   quiescent power supply current I_{Qi}, to obtain a

regression line. A gradient S_c of the regression line is

obtained by, for example, a root mean square, and a

predicted coefficient K_{HI} is calculated by using the

gradient S_c and the regression line expressed by the

5   formula (7-2).

A decision coefficient r_c^2 is calculated by the

following formula.

$$r_c^2 = 1 - \frac{\Sigma(K_{Ni} - K_{Hi})^2}{\Sigma(I_{PQi})^2} \qquad \text{... (7B)}$$

10

When the condition that the decision coefficient r_c^2

is greater than a preset lower limit L_{RC}^2 and the

condition that the difference $(S_c/Iq-1)$ of the ratio

S_c/Iq and 1 is in a preset allowable range are satisfied,

15   it is determined that the two CMOS integrated circuits

resemble each other in vector waveform and the CMOS

integrated circuit under test can be sorted out as

defect-free.

Determination of Defect or Defect-free - 4

20   A normalized value $R_{Li} = (I_{Li}-I_\ell)/\sigma_L$ is calculated in

advance for a plurality of defect-free CMOS integrated

circuits based on the normal leakage current I_{Li} at each

vector point and its mean value I_ℓ and standard deviation

σ_L. The normalized values R_{Li} are averaged for the

plurality of CMOS integrated circuits to calculate an average normalized value R_{Ni}.

The coefficient $R_{Li} (= (L_{Li} - I_1)/\sigma_1)$ is a normalized value of the normal leakage current deviation I_{PLi} by the

5   standard deviation σ_1 of normal leakage current I_{Li}.

The calculation of the average coefficient R_{Ni} from the plurality of the coefficients R_{Li} is intended to increase an accuracy of the coefficient R_{Ni}. Therefore, the coefficient R_{Li} of one reference CMOS IC can be

10   applied in the following descriptions and equations.

Next, the mean value Iq and deviation I_{DQi} ($= I_{Qi} - Iq$) and the standard deviation σ_Q and standard deviation $R_{Qi} = I_{DQi}/\sigma_Q$ are calculated from the measured value I_{Qi} of the CMOS integrated circuit under test.

15   The regression analysis is performed on the coefficient R_{Ni} and R_{Qi} to obtain a regression line. A gradient S_D of the regression line is obtained by, for example, a root mean square, and a predicted coefficient R_{HI} is calculated by using the gradient S_D and the

20   regression line expressed by the formula (7-2).

A decision coefficient r_D^2 is calculated by the formula (7A).

When the condition that the decision coefficient r_D^2 is greater than a preset lower limit L_{RD}^2 and the

25   condition that the difference $(S_D - 1)$ of the slant S_D of

the regression line and 1 is in a preset allowable range

are satisfied, it is determined that the two CMOS

integrated circuits resemble each other in vector

waveform and the CMOS integrated circuit under test can

5   be sorted out as defect-free.

Determination of Defect or Defect-free - 5 (Two-

Point Test Method)

With a functional test of CMOS integrated circuits,

it is possible to detect about 60 to 80 percent of the

10   defects by the measured value of the first vector point.

Therefore, a standby test based on measurement of one

point (one vector point) is often performed.

Below, an explanation will be made of a two-point

test method for testing CMOS integrated circuits based on

15   the measured values of two vector points.

The reference value W_{L12} obtained by dividing the

difference $(I_{L1}-I_{L2})$ between the measured value I_{L1} at the

first point and the measured value I_{L2} at the second

point by the mean value I_ℓ in a defect-free CMOS

20   integrated circuit is expressed by the following equation

(34). Note that the reference value W_{L12} corresponds to a

yardstick of the extent of variability of the measured

values I_{L1} and I_{L2}.

$$W_{L12} = (I_{L1}-I_{L2})/I_\ell \qquad\qquad (34)$$

25

The above equation (34) can be modified as in the following equation (35) using equations (1) and (2).

$$W_{L12} = \{(R_1 \cdot Ip + I_{AL}) - (R_2 \cdot Ip + I_{AL})\} / (Ip + I_{AL})$$
$$= (R_1 - R_2) \cdot Ip / (Ip + I_{AL}) \qquad (35)$$

When I_{AL} is 0 or substantially 0 in the above equation (35), the following equation (36) is obtained.

$$W_{L12} = R_1 - R_2 \qquad (36)$$

In this way, the reference value W_{L12} becomes the difference of the proportional coefficients R_1 and R_2 and becomes a constant value, so the reference value W_{L12} can be found in advance from the measured values I_{L1} and I_{L2} of a defect-free CMOS integrated circuit.

When the measured value I_{Q1} of the quiescent power supply current of a CMOS integrated circuit includes a defect current, the comparative value W_{Q12} obtained by dividing the difference $(I_{Q1} - I_{Q2})$ of the measured value I_{Q1} at the first point and the measured value I_{Q2} at the second point by the mean value Iq is expressed by the following equation (37).

$$W_{Q12} = (I_{Q1} - I_{Q2}) / Iq \qquad (37)$$

The above equation (37) can be modified as in the following equation (38) using equation (3).

$$W_{Q12} = \{(I_{L1}+I_{RD1}+I_{SD})-(I_{L2}+I_{RD2}+I_{SD})\}/Iq$$

$$= (I_{L1}-I_{L2}+I_{RD1}-I_{RD2})/Iq \tag{38}$$

When I_{rd} is 0 or substantially 0 in equation (24), that is, when $I_{RD1} = I_{RD2} = 0$, the mean value Iq becomes $I_\ell+I_{SD}$. By substituting this mean value Iq in the above equation (38), the following equation (39) is obtained.

$$W_{Q12} = (I_{L1}-I_{L2})/(I_\ell+I_{SD}) \tag{39}$$

From the above equation (39) and equation (34), the following equation (40) is obtained.

$$W_{Q12} < W_{L12} \tag{40}$$

On the other hand, when I_{SD} is 0 or substantially 0 in equation (24), the mean value Iq becomes $I_\ell+I_{rd}$. Further, when $I_{rd} \ll I_\ell$, $Iq \fallingdotseq I_\ell$. It is possible to modify the above equation (38) to the following equation (41) using the equation of this mean value Iq.

$$W_{Q12} \fallingdotseq (I_{L1}-I_{L2})/I_\ell+(I_{RD1}-I_{RD2})/I_\ell$$

$$= W_{L12}+(I_{RD1}-I_{RD2})/I_\ell \tag{41}$$

According to the above equation (41), the relative magnitudes of the value W_{Q12} and W_{L12} change according to the relative magnitudes of the defect currents I_{RD1} and I_{RD2}. From these relationships, the condition for a

defect-free circuit may be made that the difference

between the reference value W_{L12} and the comparative value

W_{Q12} $(W_{Q12}-W_{L12})$ be within a preset allowable range. The

condition for a defect-free device can be expressed using

5   the upper limit T_{12}.

$$|W_{Q12}-W_{L12}|<T_{12} \qquad\qquad (42)$$

Tester

FIG. 9 is a view of showing the configuration of a

10   tester for carrying out the method of determination of a

defect-free CMOS integrated circuit according to the

present invention. This tester 30 has a measuring

instrument 10 and a computer 20 and conducts a functional

test on the CMOS integrated circuits 50_1 to 50_N.

15   The measuring instrument 10 measures the quiescent

power supply current I_{DDQ} for the CMOS integrated circuits

50_1 to 50_N for each of the vector points $\underline{i}$ and supplies

the measured value I_{Qi} to the computer 20.

The computer 20 has a control device, a storage

20   device, an input device, and an output device. The

control device of the computer 20 processes the measured

value I_{Qi} from the measuring instrument 10 in various

ways, determines defect (defect or defect-free) and

inspects the resemblance of the CMOS integrated circuits

25   50_1 to 50_N based on the results of processing, and

outputs the results of determination of defect (defect or defect-free) and the results of inspection of resemblance to the output device.

Access to the storage device of the computer 20 is 5 controlled by the control device. This storage device stores the measured values of the defect-free CMOS integrated circuits and the measured value I_{Qi} of the vector points $\underline{i}$ of the CMOS integrated circuits 50_1 to 50_N. Note that the storage device may also be configured 10 to store in advance the measured value I_{Li} of defect-free CMOS integrated circuits before measuring the quiescent power supply current I_{DDQ} of the CMOS integrated circuits 50_1 to 50_N.

Method of Determination of Defect-Free Device

15 Next, the method of determination of a defect-free CMOS integrated circuit will be explained by the method of selection out a defect-free circuit and the method of determination of defect (defect or defect-free).

In the method of selection out a defect-free 20 circuit, a defect-free circuit is sorted out from a group of CMOS integrated circuits under test based on the measured value I_{Qi} of the quiescent power supply current for the CMOS integrated circuits under test (DUT).

On the other hand, in the method of determination of 25 defect (defect of defect-free), it is determined if a

CMOS integrated circuit under test is a defect-free

circuit based on the measured value I_{Li} of quiescent

power supply current of defect-free CMOS integrated

circuits and the measured value I_{Qi} of quiescent power

5   supply current of the CMOS integrated circuit under test.

The defect-free CMOS integrated circuits are defined for

example as defect-free CMOS integrated circuits obtained

by the method of selection out a defect-free circuit.

Method of Selection Out Defect-Free Devices

10   FIG. 10 is a flow chart of processing of the

computer 20 in the tester 30 of FIG. 9 and shows an

embodiment of the method of selection out a defect-free

CMOS integrated circuit. Note that at the start stage, it

is assumed that the measured values I_{Qi} of quiescent

15   power supply current of the CMOS integrated circuits 50_1

to 50_N have been obtained.

Step 1: Provisional Selection of Reference IC

At step S1, one CMOS integrated circuit is extracted

from the group of CMOS integrated circuits 50_1 to 50_N to

20   be sorted (group of selection ICs) and designated as the

reference IC. This reference IC is removed from the group

of selection ICs.

Step 2: Resemble Test

At step S2, the remaining devices of the group of

25   selection ICs are successively designated as comparative

ICs and inspected for resemblance of vector waveforms

with the reference IC.

Step 3: Comparison

At step S3, it is determined if there is a

5   comparative IC with a resembling vector waveform in the

group of selection ICs inspected for resemblance.

Step 4: determination

When there is no comparative IC having a resembling

vector waveform, the routine proceeds to step S4, where

10   it is determined that the reference IC is defective.

When there is a comparative IC having a resembling

vector waveform, the routine proceeds to step S5, where

it is determined that the comparative IC is defect-free

and that comparative IC is removed from the group of

15   selection ICs.

These steps S1 to S5 are repeated until the number

of remaining circuits of the group of selection ICs

becomes 1 or 0 so as to thereby enable selection out of

defect-free devices.

20   Note that at step S5, by collecting the comparative

ICs for each reference IC, it is possible to classify the

defect-free circuits by the differences in waveforms.

First Example of Resemble Test

FIG. 11 is a flow chart of a first embodiment of

25   processing for inspection of resemblance at step S2 of

FIG. 10.

First, at step S11, the deviation I_{DQxi} (= I_{Qxi}-Iqx) is calculated for the measured value I_{Qxi} of the quiescent power supply current of the reference IC and the

5   deviation I_{DQyi} (= I_{Qyi}-Iqy) is calculated based on the measured value I_{Qyi} of the quiescent power supply current of the comparative IC.

Here, Iqx is the mean value obtained by averaging the measured value I_{Qxi} for all vector points $\underline{n}$, while Iqy

10   is the mean value obtained by averaging the measured value I_{Qyi} for all vector points $\underline{n}$.

At step S12, regression analysis is performed on the deviations (I_{DQxi} and I_{DQyi}) to obtain a regression line.

A gradient S_A of the regression line is obtained by,

15   for example, a root mean square, and a predicted quiescent power supply current I_{Hi} is calculated by using the gradient S_A and the regression line expressed by the formula (7-2).

A decision coefficient $r_A{}^2$ is calculated by the

20   formula (7).

At step S13, when $L_{RA}{}^2 < r_A{}^2$ and $|S_A-Iqy/Iqx| < L_{SA}$, it is determined that the vector waveforms of the comparative IC and reference IC resemble each other.

Here, $L_{RA}{}^2$ is the lower limit of the decision

25   coefficient $r_A{}^2$, while L_{SA} is the upper limit

corresponding to the allowable range of deviation from the slant S_A.

Second Example of Resemble Test

FIG. 12 is a flow chart of a second embodiment of processing for inspection of resemblance at step S2 of FIG. 10.

First, at step S21, the normalized value $R_{Qxi} = (I_{Qxi}-Iqx)/\sigma_{Qx}$ is calculated based on a measured value I_{Qxi} of the quiescent power supply current of the reference IC, while the normalized value $R_{Qyi} = (I_{Qyi}-Iqy)/\sigma_{Qy}$ is calculated based on the measured value I_{Qyi} of the quiescent power supply current of the comparative IC.

Here, σ_{Qx} is the standard deviation of the measured value I_{Qxi}, while σ_{Qy} is the standard deviation of the measured value I_{Qyi}.

At step S22, regression analysis is performed on the normalized values (R_{Qxi} and R_{Qyi}) to obtain a regression line.

A gradient S_B of the regression line is obtained by, for example, a root mean square, and a predicted normalized value R_{Hi} is calculated by using the gradient S_B and the regression line expressed by the formula (7-2).

A decision coefficient $r_B{}^2$ is calculated by the formula (7A).

At step S23, when $L_{RB}{}^2 < r_B{}^2$ and $|S_B - I| < L_{SB}$, it is

determined that the vector waveforms of the comparative

IC and reference IC resemble each other.

Here, $L_{RB}{}^2$ is the lower limit of the decision

5 coefficient $r_B{}^2$, while L_{SB} is the upper limit

corresponding to the allowable range of deviation from

the slant S_B.

Third Example of Resemble Test

FIG. 13 is a flow chart of a third embodiment of the

10 processing for inspection for resemblance at step S2 of

FIG. 10.

First, at step S31, the mean values Iq and standard

deviations σ_Q of measured values of quiescent power

supply current of a group of selection ICs including the

15 reference IC and comparative ICs are calculated and a

plotted graph of (Iq and σ_Q) is prepared. For example, a

plotted graph having an abscissa indicating the mean

value Iq and an ordinate indicating the standard

deviation σ_Q and including plotted points indicating the

20 (Iq and σ_Q) of the CMOS integrated circuits is prepared.

At step S32, the line where the plotted points

concentrate in the plotted graph is found. When the two

plotted points corresponding to the reference IC and

comparative IC are positioned in an allowable range from

25 that line (for example, within a predetermined distance),

it is determined that the waveforms of the reference IC

and comparative IC resemble each other.

Note that the flow chart of FIG. 13 can be used when

extracting defect-free CMOS integrated circuits from the

5   group of selection ICs.

For example, the mean values Iq and standard

deviations σ_Q of the measured values I_{Qi} of the group of

selection ICs are calculated, a plotted graph of (Iq and

σ_Q) is prepared, and it is determined that the CMOS

10   integrated circuit corresponding to a plot positioned in

an allowable range from the line where the plotted points

concentrate in the plotted graph is defect-free.

Fourth Example of Resemble Test

FIG. 14 is a flow chart of a fourth embodiment of

15   the processing for inspection of resemblance at step S2

in FIG. 10.

First, at step S41, the mean values Iq and

deviations I_{DQi} of the measured values of the quiescent

power supply current of the group of selection ICs

20   including the reference IC and comparative ICs are

calculated and a plotted graph of (Iq and I_{DQi}) is

prepared. For example, a plotted graph having an abscissa

indicating the mean value Iq and an ordinate indicating

the deviation I_{DQi} and including plotted points indicating

25   (Iq and I_{DQi}) of the CMOS integrated circuits is prepared.

At step S42, the line where the plotted points concentrate in the plotted graph is found. When the two plotted points corresponding to the reference IC and comparative IC are positioned in an allowable range from

5   that line (for example, within a predetermined distance), it is determined that the waveforms of the reference IC and comparative IC resemble each other.

Note that the flow chart of FIG. 14 can be used when extracting defect-free CMOS integrated circuits from the

10   group of selection ICs.

For example, the mean values Iq and standard deviations I_{DQi} of the measured values I_{Qi} of the group of selection ICs are calculated, a plotted graph of (Iq and I_{DQi}) is prepared, and it is determined that a CMOS

15   integrated circuit corresponding to a plot positioned in an allowable range from the line where the plotted points concentrate in the plotted graph is defect-free.

Method of Determination of Defect or Defect-free

Preferred embodiments of the determination of

20   defect-free or defect IC will be described.

First Embodiment of Determination

FIG. 15 is a flow chart of a first embodiment of a method of determination of defect (defect or defect-free). This method of determination of defect determines

25   that an integrated circuit device under test (DUT) is

defect-free when the computer 20 of the tester 30 of FIG. 9 holds the measured values I_{Li} of defect-free CMOS integrated circuits.

First, at step S51, the coefficients $K_{Li} = (I_{Li} - I_\ell)/I_\ell$

5   at all of the vector points $\underline{i}$ are calculated from a group of defect-free CMOS integrated circuits (group of ICs) and the coefficients K_{Li} are averaged for the group of defect-free ICs to calculate a reference coefficient K_{Ni}. Note that the coefficients K_{Li} are values obtained by

10   normalizing the deviation $(I_{Li} - I_\ell)$ of the measured value I_{Li} by the mean value I_ℓ.

The calculation of the average coefficient K_{Ni} from the plurality of the coefficients K_{Li} is intended to increase an accuracy of the coefficient K_{Ni}. Therefore,

15   the coefficient K_{Li} of one reference CMOS IC can be applied in the following descriptions and equations.

At step S52, the deviation $I_{DQi} = I_{Qi} - Iq$ is calculated from a measured value I_{Qi} of the quiescent power supply current of the IC device under test (DUT).

20   At the step S53, the regression analysis is performed on the coefficient K_{Ni} and the deviation I_{PQi} of the measured quiescent power supply current I_{Qi}, to obtain a regression line. A gradient S_c of the regression line is obtained by, for example, a root mean square, and

25   a predicted coefficient K_{HI} is calculated by using the

gradient S_c and the regression line expressed by the

formula (7-2).

A decision coefficient R_c^2 is calculated by the

formula (7B).

5   At step S54, when $L_{RC}^2 < r_c^2$ and $|S_c/Iq-1| < L_{SC}$ are

satisfied, it is determined that the IC device under test

is defect-free, while when they are not satisfied, it is

determined that the device under test is defective.

Here, L_{RC}^2 is the lower limit of the decision

10   coefficient R_c^2, while L_{SC} is the upper limit

corresponding to the allowable range of deviation from

the slant S_c.

Second Embodiment of Determination

FIG. 16 is a flow chart of a second embodiment of

15   the method of determination of defect (defect or defect-

free). This method of determination of defect determines

that an IC device under test (DUT) is defect-free when

the computer 20 of the tester 30 of FIG. 9 holds the

measured values I_{Li} of defect-free CMOS integrated

20   circuits.

First, at step S61, the normalized values $R_{Li} = (I_{Li} -$

$I_\ell)/\sigma_L$ at all of the vector points $\underline{i}$ are calculated from a

group of defect-free CMOS integrated circuits (IC group),

and the normalized values R_{Li} are averaged for the group

25   of defect-free ICs to calculate an average normalized

value R_{Ni}.

The normalized value $R_{Li} (= (L_{Li} - I_1)/\sigma_1)$ is a normalized value of the normal leakage current deviation I_{PLi} by the standard variation σ_1 of I_{Li}.

5   The calculation of the average normalized value R_{Ni} from the plurality of the coefficients K_{Li} is intended to increase an accuracy of thenormalized value R_{Ni}. Therefore, the normalized value R_{Li} of one reference CMOS IC can be applied in the following descriptions and 10   equations.

At step S62, the normalized value $R_{Qi} = (I_{Qi} - Iq)/\sigma_Q$ is calculated from the measured value I_{Qi} of the quiescent power supply current of the IC device under test (DUT).

At the step S62, the regression analysis is 15   performed on the coefficient K_{Ni} and the deviation I_{PQi} of the measured quiescent power supply current I_{Qi}, to obtain a regression line. A gradient S_D of the regression line is obtained by, for example, a root mean square, and a predicted normalizes value R_{Hi} is calculated by using 20   the gradient S_D and the regression line expressed by the formula (7-2).

A decision coefficient r_D^2 is calculated by the formula (7B).

At step S64, when $L_{RD}^2 < r_D^2$ and $|S_D - 1| < L_{SD}$ are 25   satisfied, it is determined that the IC device under test

is defect-free, while when they are not satisfied, it is determined that it is defective.

Here, L_{RD}^2 is the lower limit of the decision coefficient r_D^2, while L_{SD} is the lower limit corresponding to the allowable range of deviation from the slant S_D.

Third Embodiment of Determination

FIG. 17 is a flow chart of a third embodiment of the method of determination of defect. This method of determination of defect (defect or defect-free) determines that a device under test (DUT) is defect-free when the computer 20 of the tester 30 of FIG. 9 holds the measured values I_{Li} of defect-free CMOS integrated circuits.

First, at step S71, the normalized values $R_{Li} = (I_{Li} - I_t)/\sigma_L$ at all of the vector points $\underline{i}$ are calculated from a group of defect-free CMOS integrated circuits (IC group), and the normalized values R_{Li} are averaged for the group of defect-free ICs to calculate an average normalized value R_{Ni}.

The calculation of the average normalized value R_{Nc} from the plurality of the coefficients R_{Li} is intended to increase an accuracy of the value R_{Li}. Therefore, the value R_{Li} of one reference CMOS IC can be applied in the following descriptions and equations.

At step S72, a maximum value E_{MAX} giving $|I_{Li}-I_{\ell}-R_{Ni}\cdot\sigma_L|<E_{MAX}$ is found.

At step S73, the mean value Iq and standard deviation σ_Q are calculated from the measured value I_{Qi} of the IC device under test.

At step S74, when $|I_{Qi}-Iq-R_{Ni}\cdot\sigma_Q|<E_{MAX}$ is satisfied, it is determined that the IC device under test is defect-free, while when it is not satisfied, it is determined that the IC device under test is defective.

Fourth Embodiment of Determination

FIG. 18 is a flow chart of a fourth embodiment of the method of determination of defect (defect of defect-free). This method of determination of defect determines that an IC device under test (DUT) is defect-free when the computer 20 of the tester 30 of FIG. 9 holds the measured values I_{Li} of defect-free CMOS integrated circuits.

First, at step S81, the mean values I_{ℓ} and the standard deviations σ_L are calculated for a group of defect-free CMOS integrated circuits (IC group).

At step S82, a plotted graph of (σ_L and I_{ℓ}) is prepared, the slant of the line at which the plotted points concentrate is found, and that slant is made ($1/\sigma_R$). For example, a plotted graph having an abscissa (x-axis) showing the standard deviation σ_L and an

ordinate (y-axis) showing the mean value I_ℓ and including

plotted points showing the standard deviation σ_L and mean

value I_ℓ is prepared.

At step S83, the mean value Iq and standard

deviation σ_Q are calculated from measured value I_{Qi} of the

IC device under test.

At step S84, when $Iq - \sigma_Q / \sigma_R < L_{SE}$ is satisfied, it is

determined that the IC device under test is defect-free,

while when it is not satisfied, it is determined that the

IC device under test is defective. Note that L_{SE} is the

upper limit corresponding to the allowable range of error

between a mean value Iq and the value σ_Q / σ_R.

Fifth Embodiment of Determination

FIG. 19 is a flow chart of a fifth embodiment of the

method of determination of defect. This method of

determination of defect determines that a device under

test (DUT) is defect-free when the computer 20 of the

tester 30 of FIG. 9 holds measured values I_{L1} and I_{L2} of

two vector points of a defect-free CMOS integrated

circuit.

First, at step S91, the reference value $W_{L12} = (I_{Li} -$

$I_{L2})/I_\ell$ obtained by dividing the difference of the

measured values I_{L1} and I_{L2} by the mean value I_ℓ is

calculated for a defect-free CMOS integrated circuit.

At step S92, a comparative value $W_{Q12} = (I_{Q1} - I_{Q2})/Iq$

obtained by dividing the difference of the measured

values I_{Q1} and I_{Q2} of the two vector points by the mean

value Iq is calculated for the IC device under test.

At step S93, when $|W_{Q12}-W_{L12}|<T_{12}$ is satisfied, it is

5 determined that the IC device under test is defect-free,

while when it is not satisfied, it is determined to be

defective. Note that T_{12} is the upper limit showing the

allowable range of the difference between the comparative

value W_{Q12} and reference value W_{L12}.

10 <u>Sixth Embodiment of Determination</u>

FIG. 20 is a flow chart of a sixth embodiment of the

method of determination defect or defect-free. This

method of determination of defect determines that an IC

device under test (DUT) is defect-free when the computer

15 20 of the tester 30 in FIG. 9 holds the measured values

I_{Li} of defect-free CMOS integrated circuits.

First, at step S101, the mean values I_{ℓ} and the

deviations I_{DLl} are calculated for each IC in a group of

defect-free CMOS integrated circuits (IC group), and a

20 total mean value and total deviations are calculated for

the group of ICs.

The coefficient $K_{Li}(=(L_{Li}-I_1)/I_1)$ is a normalized

value of the normal leakage current deviation I_{PLi} by the

average current I_1 of normal leakage current I_{Li}.

25 The calculation of the total average and total

deviations is intended to increase an accuracy of the same. Therefore, the average and deviation of one reference CMOS IC can be applied in the following descriptions and equations.

5   At step S102, a plotted graph of (I_ℓ and I_{DL1}) is prepared and the line at which the plotted points concentrate (ideal line) is found. For example, a plotted graph having an abscissa (x-axis) showing the mean value I_ℓ and an ordinate (y-axis) showing the deviation I_{DL1} and

10   including plotted points showing the mean value I_ℓ and deviation I_{DL1} is prepared. It is possible to find the (R_i-1) in equation (18) from the slant of the ideal line and possible to find the $(1-R_i) \cdot I_{AL}$ in equation (18) from the y section from this plotted graph.

15   At step S103, the mean value Iq and deviation $I_{DQi} = I_{Qi}-Iq$ are calculated from the measured value I_{Qi} of the device under test.

At step S105, when $|I_{DQi}-J_{DQi}|<T_D$ is satisfied, it is determined that the IC device under test is defect-free,

20   while when it is not satisfied, it is determined that the IC device under test is defective. Note that T_D is the upper limit corresponding to the allowable range of error between a deviation I_{DQi} and predicted deviation J_{DQi}.

In the above description, the CMOS IC is discussed

25   as an example, however, the present invention can be

applied a variety of semiconductor IC.

Summarizing the effects of the present invention, it is possible to provide a method and apparatus for determination of a defect-free CMOS integrated circuit

5 enabling determination of a defect-free state without regard as to the presence of a circuit leakage current.

While the invention has been described with reference to specific embodiments chosen for purpose of illustration, it should be apparent that numerous

10 modifications could be made thereto by those skilled in the art without departing from the basic concept and scope of the invention.